

A theorem for the beam splitter entangler

Wang Xiang-bin*

Imai Quantum Computation and Information project, ERATO, Japan Sci. and Tech.
Corp.

Daini Hongo White Bldg. 201, 5-28-3, Hongo, Bunkyo, Tokyo 113-0033, Japan

Abstract

It is conjectured that the an entanglement output states from a beam splitter requires the non-classicality in the input state(M.S. Kim, W. Son, V. Buzek and P. L. Knight, Phys. Rev. A, 65, 032323(2002)). Here we give a proof for this conjecture.

The beam splitter is one of the few quantum devices that may act as the entangler. The entangler properties of a beam splitter have been studied in the past [2–5]. In particular, Kim et al [5] studied the entangler property with many different input states such as the Fock number state, the coherent state, the squeezed state and the mixed states in Gaussian form. It has been conjectured there that, to obtain an entangled output state, a necessary condition is that the input state should be non-classical. Unfortunately, there is no proof for this conjecture. In this paper, we give a very simple proof for this conjecture.

Consider a loseless beam splitter(see figure 1). We can distinguish the field mode a and mode b by the different propagating direction. Most generally, the property of a beam splitter operator $\hat{B}$ in Schrodinger picture can be summarized by the following equations(see e.g., ref [1])

$$\rho_{out} = \hat{B}\rho_{in}\hat{B}^{-1}, \quad (1)$$

*email: wang@qci.jst.go.jp

$$\hat{B}^\dagger = \hat{B}^{-1}, \quad (2)$$

$$\hat{B} \begin{pmatrix} \hat{a} \\ \hat{b} \end{pmatrix} \hat{B}^{-1} = M_B \begin{pmatrix} \hat{a} \\ \hat{b} \end{pmatrix}, \quad (3)$$

$$M_B = \begin{pmatrix} \cos \theta e^{i\phi_0} & \sin \theta e^{i\phi_1} \\ -\sin \theta e^{-i\phi_1} & \cos \theta e^{-i\phi_0} \end{pmatrix} \quad (4)$$

$$\hat{B}|00\rangle = |00\rangle. \quad (5)$$

Here ρ_{in} and ρ_{out} are the density operator for the input and output states respectively. Both of them are two mode states including mode a and mode b . The elements in the matrix M_B are determined by the beam splitter itself, $\hat{a}, \hat{b}$ are the annihilation operators for mode a and mode b respective, $|00\rangle$ is the vacuum state for both mode. Equation (5) is due to the simple fact of no input no output. Without any loss of generality, we can express ρ_{in} by the P representation in the following form:

$$\rho_{in} = \int_{-\infty}^{\infty} P(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*) |\alpha_a, \alpha_b\rangle \langle \alpha_a, \alpha_b| d^2\alpha_a d^2\alpha_b, \quad (6)$$

where $|\alpha_a, \alpha_b\rangle$ is the coherent state in two mode Fock space, i.e.

$$|\alpha_a, \alpha_b\rangle = \hat{D}_{ab}(\alpha_a, \alpha_b)|00\rangle \quad (7)$$

and

$$\hat{D}_{ab}(\alpha_a, \alpha_b) = e^{\hat{a}^\dagger \alpha_a - \hat{a} \alpha_a^* + \hat{b}^\dagger \alpha_b - \hat{b} \alpha_b^*}. \quad (8)$$

If ρ_{in} is a classical state, the distribution function $P(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*)$ must be non-negative definite in the whole complex planes. In such a case, the output state is

$$\rho_{out} = \int_{-\infty}^{\infty} P(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*) \hat{B} |\alpha_a, \alpha_b\rangle \langle \alpha_a, \alpha_b| \hat{B}^{-1} d^2\alpha_a d^2\alpha_b \quad (9)$$

which is equivalent to

$$\rho_{out} = \int_{-\infty}^{\infty} P(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*) \hat{B} \hat{D}_{ab}(\alpha_a, \alpha_b) \hat{B}^{-1} \cdot \hat{B} |00\rangle \langle 00| \hat{B}^{-1} \cdot \hat{B} \hat{D}_{ab} \hat{B}^\dagger. \quad (10)$$

From equation(5) we know that $\hat{B}|00\rangle \langle 00| \hat{B}^{-1} = |00\rangle \langle 00|$. By equation(3) we can see that

$$\hat{B} \hat{D}_{ab}(\alpha_a, \alpha_b) \hat{B}^{-1} = \hat{D}_{ab}(\alpha'_a, \alpha'_b) \quad (11)$$

and

$$(\alpha'_a, \alpha'_b) = (\alpha_a, \alpha_b) M_B. \quad (12)$$

In short, the following equatoin can be easily obtained by equation(3,4,5)

$$\hat{B} |\alpha_a, \alpha_b\rangle \langle \alpha_a, \alpha_b| \hat{B}^{-1} = |\alpha'_a, \alpha'_b\rangle \langle \alpha'_a, \alpha'_b| \quad (13)$$

Since $\det M_B = 1$, we have the following formula for the output state

$$\rho_{out} = \int_{-\infty}^{\infty} P(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*) |\alpha'_a, \alpha'_b\rangle \langle \alpha'_a, \alpha'_b| d^2 \alpha'_a d^2 \alpha'_b. \quad (14)$$

This is equivalent to

$$\rho_{out} = \int_{-\infty}^{\infty} P'(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*) |\alpha_a, \alpha_b\rangle \langle \alpha_a, \alpha_b| d^2 \alpha_a d^2 \alpha_b \quad (15)$$

and

$$P'(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*) = P(\alpha''_a, \alpha''_b, \alpha''_a^*, \alpha''_b^*) \quad (16)$$

and

$$(\alpha''_a, \alpha''_b) = (\alpha''_a, \alpha''_b) M_B^{-1}. \quad (17)$$

Since $P(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*)$ is non-negative, functional $P'(\alpha_a, \alpha_b, \alpha_a^*, \alpha_b^*)$ must be also non-negative. By the definition of separability, state ρ_{out} defined by equation(15) must be separable. Therefore we have the following theorem:

Theorem: *If the input state is a classical state, the output state of a beam splitter must be a separable state.*

This is equivalent to say, in order to obtain an entangled output state, the non-classicality

of the input state is a necessary condition. This theorem can be extended to a more general situation in the *multimode* Fock space. Let's consider the rotation operator $\hat{R}$ in n -mode Fock space. We have

$$\hat{R}\Lambda\hat{R}^{-1} = M_R\Lambda, \quad (18)$$

where $\Lambda = (\hat{c}_1, \hat{c}_2 \cdots \hat{c}_n)^T$, $\hat{c}_i$ are the annihilation operators of the i 'th mode and M_R is a n -dimensional unitary matrix. By using the BCH formula

$$e^\mu \nu e^{-\mu} = \nu + [\mu, \nu] + \frac{1}{2!}[\mu, [\mu, \nu]] + \cdots \quad (19)$$

we have the following explicitly formula for the operator $\hat{R}$:

$$\hat{R} = \exp\left(-\Lambda^\dagger \ln M_R \Lambda\right). \quad (20)$$

Therefore we know that

$$\hat{R}|00 \cdots 0\rangle = |00 \cdots 0\rangle. \quad (21)$$

Any classical multimode state in Fock space can be written in the following probabilistic distribution

$$\rho = \int_{-\infty}^{\infty} \mathbf{P}(\alpha, \alpha^*) |\alpha\rangle \langle \alpha| d^2\alpha, \quad (22)$$

where $|\alpha\rangle = |\alpha_1 \alpha_2 \cdots \alpha_n\rangle$ and $\mathbf{P}(\alpha, \alpha^*)$ is a non-negative functional provided that ρ is a classical state. Similar to the two mode case, we can shown that,

$$\rho = \int_{-\infty}^{\infty} \mathbf{P}'(\alpha, \alpha^*) |\alpha\rangle \langle \alpha| d^2\alpha, \quad (23)$$

and

$$\mathbf{P}'(\alpha, \alpha^*) = \mathbf{P}(\alpha'', \alpha''^*) \quad (24)$$

and

$$(\alpha'') = (\alpha) \cdot M_R^{-1}. \quad (25)$$

Obviously, the functional $\mathbf{P}'(\alpha, \alpha^*)$ is non-negative. Thus we draw the following conclusion in the multimode Fock space: *A classical density operator in the multimode Fock space is separable under arbitrary rotation.*

Although the nonclassicality in the input state is a necessary condition, it is obviously not a sufficient condition for the entanglement in the output state of a beam splitter. Since a beam splitter operator is unitary, it is reversible. It has been shown in ref [5] that nonclassical separable input state can be changed to an entangled state in the output. The inverse of such a process makes examples that even though the input state is nonclassical, the output could be still separable. Some specific examples are given in [7].

I thank Prof Imai for support. I thank Dr Huang WY, Dr Winter, Dr Yura H, Dr Matsumoto K, and Dr Tomita A for useful discussions.

REFERENCES

- [1] R. A. Campos, B. E. A. Saleh and M. C. Teich, Phys. Rev. A, 40, 1371(1989).
- [2] S. M. Tan, D. F. Walls, and M. J. Collett, Phys. Rev. Lett. 77, 285(1990).
- [3] B. C. Sanders, Phys. Rev. A 45, 6811(1992); B. C. Sanders, K. S. Lee, and M. S. Kim, *ibid*, 52, 735(1995); S. Scheel *et al*, Phys. Rev. A 62, 043803.
- [4] M. G. A. Paris, Phys. Rev. A 59, 1615(1999).
- [5] M. S. Kim, W. Son, V. Buzek, and P. L. Knight, Phys. Rev. A 65, 032323(2002).
- [6] D. F. Walls and G. J. Milburn, Quantum Optics, Springer-Verlag, 1994.
- [7] R. A. Campos, Phys. Rev. A, 62, 013809(2000).

FIGURES




FIG. 1. A schematic diagram for the beamsplitter operation. Both the input and the output are two mode states. The different mode is distinguished by the propagating direction of the field.